# Yuasa Technical Data Sheet

## Yuasa NP1.2-12 Industrial VRLA Battery

| s | p | e | С | if | ic | :a | ti | ο | n   | s |  |
|---|---|---|---|----|----|----|----|---|-----|---|--|
| - | μ | - | • | •• |    |    |    | 0 | ••• | 5 |  |

| <b>Specifications</b><br>Nominal voltage (V)<br>20-hr rate Capacity to 10.5V at 20°C (Ah)<br>10-hr rate Capacity to 10.8V at 20°C (Ah)   | 12<br>1.2<br>1.1   |
|--|--|
| <b>Dimensions</b><br>Length (mm)<br>Width (mm)<br>Height over terminals (mm)<br>Mass (kg)  | 97 (±1)<br>48 (±1)<br>54.5 (±2)<br>0.58                      |
| <b>Terminal Type</b><br>FASTON - Quickfit / release (JST where stated)   | 4.75   |
| <b>Operating Temperature Range</b><br>Storage (in fully charged condition)<br>Charge<br>Discharge  | -20°C to +60°C<br>-15°C to +50°C<br>-20°C to +60°C           |
| <b>Storage</b><br>Capacity loss per month at 20°C (% approx.)  | 3  |
| <b>Case Material</b><br>Standard   | ABS (UL94:HB)  |
| <b>Charge Voltage</b><br>Float charge voltage at 20°C (V)/Block<br>Float charge voltage at 20°C (V)/Cell<br>Float Chg voltage tmp correction factor from std<br>20°C (mV)<br>Cyclic (or Boost) charge Voltage at 20°C (V)/Block<br>Cyclic (or Boost) charge Voltage at 20°C (V)/Cell | 13.65 (±1%)<br>2.275 (±1%)<br>-3<br>14.5 (±3%)<br>2.42 (±3%) |
| Cyclic Chg voltage tmp correction factor from std 20°C (mV)  | -4   |
| <b>Charge Current</b><br>Float charge current limit (A)<br>Cyclic (or Boost) charge current limit (A)  | No limit<br>0.3  |
| <b>Maximum Discharge Current</b><br>1 second (A)<br>1 minute (A)   | 36<br>12   |
| <b>Impedance</b><br>Measured at 1 kHz (mΩ)   | 110  |
| <b>Design Life &amp; Approvals</b><br>EUROBAT Classification: Standard Commercial<br>Yuasa design life at 20°C (yrs)<br>VdS (Germany)  | 3 to 5 years<br>up to 5<br>VdS No: G 101094                  |
|  |  |





### Layout

| Θ        |  |
|----------|--|
| $\oplus$ |  |

#### 3rd Party Certifications

ISO9001 - Quality Management Systems UNDERWRITERS LABORATORIES Inc.

# Safety

#### Installation

Can be installed and operated in any orientation except permanently inverted.

# Handles

Batteries must not be suspended by their handles (where fitted).

# Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

## Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.



Data Sheet generated on 13/01/2021 – E&OE

The world's leading battery manufacturer www

www.yuasaeurope.com

